
Flush mounted boxes

Installation boxes, flush



Multifix Modulo



connection

interface

Knock-outs.

various sizes

Description

Multifix Modulo is a range of installation boxes with knock-outs from Schneider Electric.

The round apparatus box is available in two depths, 46 and 61 mm (external measures). The junction box is either round with snap-fitted cover or square with screw-fixed cover. Both apparatus and junction boxes are intended for mounting in brick walls. They are also available as DIY products.

The Multifix Modulo boxes are resistant to cold and heat and can safely be installed in most environments. All metal parts are zinc-plated to eliminate risk of corrosion, and the plastic parts withstand a glow wire test of 650°. The boxes can be used for most wiring device ranges with c/c 60 mm fixing centres.

Applications

Flush-mounted boxes for brick walls. Suitable for most environments in residential and industrial buildings.

Benefits


- Good rigidity of the box
- · No tools needed to remove knock-outs
- No risk for injuries knock-outs that are clean cut to leave neither sharp edges nor burrs
- · Smart solution knock-outs of various sizes in the same box
- Universal box handles wiring devices with c/c 60 mm fixing centres
- Meets most requirements of wiring device combinations
- · Integrated interface for connection of several boxes in a row
- Self-instructive and functional design

Technical and Material data

Material, box	PP (polypropylene)
Density	0.97 g/cm ³
Colour specification	Green RAL 6001 (box) White RAL 9010 (cover)
Degree of protection	IP30
Flame resistance	650°C
Temperature range	Operating temperature from -25°C to +60°C
Standards	 IEC 60670-1 Boxes and enclosures for electrical accessories GOST R50827-95 Installation boxes

Mounting instructions

Mounting instruction, Art.No. 20064513, is available on Pl@net.



Installation boxes, flush



Multifix Modulo

	Туре	Colour	Box dim. A/B/C (mm)		Qty per	EAN code	Internal ID-No.	Ref. No.		
	Single apparatu	is box	A/b/C (mm)	⁸ ≁ ≁ c	package		ID-NO.			
	Single-station ro mm and three Ø2	und apparatus box 20 mm. Integrated o en the boxes have o	connection interf	ace for conr	nection of two	valls. Size of knock-o or more boxes in a ro).				
00	65x45	Green	81/46/71		200/4800	3606480343209	20062610	IMT35100		
B	65x60	Green	81/61/71		120	3606480343223	20062611	IMT35101		
	Round junction	box								
		nm and three Ø20 r				be used in brick wal	ls. Size of knoo	k-outs: two Ø:		
	70x40	Green	Ø80/43		175	3606480343247	20064048	IMT35120		
		20 mm and six Ø25				to be used in brick wa	alls. Size of kno	ock-outs: two		
	100x50	Green	Ø107/51		84	3606480343261	20064050	IMT35121		
	Square junction	box								
knock-outs: Material: PP	knock-outs: eigh	Square junction box with 28 knock-outs, including white screw-fixed cover and four screws, to be used in brick walls. Size of knock-outs: eight Ø16 mm, ten Ø20 mm, two Ø25 mm and eight Ø30 mm. Degree of protection IP30. Material: PP (polypropylene).								
		ypiopylelie).								
junct	ion boxes, DIY Single apparate	Green	112/51/112		72	3606480343285	20064052	IMT35122		
unct	ion boxes, DIY Single apparatu Single-station ro mm and three Ø position also whe	Green Is box und apparatus box 20 mm. Integrated o en the boxes have o	with eight knock	ace for conr	used in brick v	3606480343285 valls. Size of knock-c or more boxes in a ro	outs: two Ø10 r	nm, three Ø16		
	ion boxes, DIY Single apparatu Single-station ro mm and three Ø	Green Is box und apparatus box 20 mm. Integrated o en the boxes have o	with eight knock	ace for conr	used in brick v	valls. Size of knock-o	outs: two Ø10 r	nm, three Ø16		
	100x100x50 tion boxes, DIY Single apparatu Single-station ro mm and three Ø position also whe Material: PP (pol	Green s box und apparatus box 20 mm. Integrated o en the boxes have o ypropylene).	with eight knock connection interf different heights.	ace for conr	used in brick v nection of two	valls. Size of knock-c or more boxes in a ro	puts: two Ø10 r ow, ensures a c	nm, three Ø16 correct flush		
	100x100x50 ion boxes, DIY Single apparatu Single-station ro mm and three Ø2 position also whe Material: PP (pol 65x45 65x60 Round junction	Green Green s box und apparatus box 20 mm. Integrated o en the boxes have o ypropylene). Green Green box	with eight knock connection interf different heights. 81/46/71 81/61/71	ace for conr For DIY.	used in brick were two of two	valls. Size of knock-co or more boxes in a ro 3606480343216 3606480343230	outs: two Ø10 r ow, ensures a o 20064046 20064047	nm, three Ø16 correct flush IMT351001 IMT351011		
	100x100x50 ion boxes, DIY Single apparatu Single-station ro mm and three Ø2 position also whe Material: PP (pol 65x45 65x60 Round junction b	Green Green s box und apparatus box 20 mm. Integrated o en the boxes have o ypropylene). Green Green box ox with eight knock m and three Ø20 r	with eight knock connection interf different heights. 81/46/71 81/61/71	ace for conr For DIY.	used in brick v nection of two 200 120 fitted cover, to	valls. Size of knock-c or more boxes in a ro 3606480343216	outs: two Ø10 r ow, ensures a o 20064046 20064047	nm, three Ø16 correct flush IMT351001 IMT351011		
	100x100x50 ion boxes, DIY Single apparatu Single-station romm and three Ø2 position also whe Material: PP (pol 65x45 65x60 Round junction b Round junction b mm, three Ø16 m	Green Green s box und apparatus box 20 mm. Integrated o en the boxes have o ypropylene). Green Green box ox with eight knock m and three Ø20 r	with eight knock connection interf different heights. 81/46/71 81/61/71	ace for conr For DIY.	used in brick v nection of two 200 120 fitted cover, to	valls. Size of knock-co or more boxes in a ro 3606480343216 3606480343230	outs: two Ø10 r ow, ensures a o 20064046 20064047	nm, three Ø16 correct flush IMT351001 IMT351011		
	100x100x50 ion boxes, DIY Single apparatu Single-station romm and three Ø2 position also whe Material: PP (pol 65x45 65x60 Round junction b mm, three Ø16 m Material: PP (pol 70x40 Round junction b	Green box ox with eight knock ma and three Ø20 r gropylene). Green	with eight knock connection interf different heights. 81/46/71 81/61/71 c-outs, including mm. Degree of pr Ø80/43 ck-outs, including	white snap- rotection IP3	used in brick v ection of two 200 120 fitted cover, to 30. For DIY. 175 o-fitted cover,	valls. Size of knock- or more boxes in a ro 3606480343216 3606480343230 be used in brick wal	buts: two Ø10 r bw, ensures a c 20064046 20064047 Is. Size of knoc 20064049	IMT351001 IMT351011 IMT351011 ik-outs: two Ø		
	100x100x50 ion boxes, DIY Single apparatu Single-station ro mm and three Ø2 position also whe Material: PP (pol 65x45 65x60 Round junction t mm, three Ø16 m Material: PP (pol 70x40 Round junction t Ø16 mm, four Ø2	Green box ox with eight knock ma and three Ø20 r gropylene). Green	with eight knock connection interf different heights. 81/46/71 81/61/71 c-outs, including mm. Degree of pr Ø80/43 ck-outs, including	white snap- rotection IP3	used in brick v ection of two 200 120 fitted cover, to 30. For DIY. 175 o-fitted cover,	valls. Size of knock- or more boxes in a ro 3606480343216 3606480343230 be used in brick wal 3606480343254	buts: two Ø10 r bw, ensures a c 20064046 20064047 Is. Size of knoc 20064049	IMT351001 IMT351011 IMT351011 ik-outs: two Ø		
	100x100x50 ion boxes, DIY Single apparatu Single-station romm and three Ø2 position also whe Material: PP (pol 65x45 65x60 Round junction to mm, three Ø16 m Material: PP (pol 70x40 Round junction to Ø16 mm, four Ø2 Material: PP (pol	Green	with eight knock connection interf different heights. 81/46/71 81/61/71 81/61/71 c-outs, including mm. Degree of pr Ø80/43 ck-outs, including mm. Degree of p	white snap- rotection IP3	used in brick v nection of two 200 120 fitted cover, to 30. For DIY. 175 	valls. Size of knock-co or more boxes in a ro 3606480343216 3606480343230 be used in brick wal 3606480343254 to be used in brick wa	buts: two Ø10 r pw, ensures a c 20064046 20064047 Is. Size of knoc 20064049 alls. Size of knoc	nm, three Ø16 correct flush IMT351001 IMT351011 :k-outs: two Ø IMT351201 pck-outs: two		
	100x100x50 ion boxes, DIY Single apparatu Single-station romm and three Ø2 position also whe Material: PP (pol 65x45 65x60 Round junction b mm, three Ø16 m Material: PP (pol 70x40 Round junction b Ø16 mm, four Ø2 Material: PP (pol 100x50 Square junction	Green	with eight knock connection interf different heights. 81/46/71 81/61/71 81/61/71 c-outs, including mm. Degree of pr Ø80/43 ck-outs, including mm. Degree of pr Ø107/51	ace for conr For DIY. white snap- rotection IP3 g white snap protection IF3	used in brick v ection of two 200 120 fitted cover, to 30. For DIY. 175 -fitted cover, - 30. 84 xed cover and	valls. Size of knock-co or more boxes in a ro 3606480343216 3606480343230 be used in brick wal 3606480343254 to be used in brick wa	buts: two Ø10 r bw, ensures a c 20064046 20064047 Is. Size of knoc 20064049 alls. Size of knoc 20064051	IMT351001 IMT351001 IMT351011 ik-outs: two Ø IMT351201 ock-outs: two		