PRODUCT DATASHEET

NiMH Battery Charger (CHVCM4)

EMEA Region

Download Instructions (multilingual)

Maxi Charger

Filergizera

NIMH BATTERY AA.AAA

ENHANCED COMMUNICATION

 Multiple colored LED lights indicate charge status











(PULSING)

BATTERY PROTECTION

· Limits damage to batteries from overcharge



SAFETY TIMER

 Ensures charger is not active for extended periods of time



Before Using Your Charger:

Please read all instructions and cautionary markings on the battery charger, batteries, and device.

Best used with *Energizer*® NiMH batteries.

Product Detail:

Designation: Maxi Charger

Model: CHVCM4

Color: Black

Charge Capability: "AA" (2) or (4) / "AAA" (2) or (4)

"AA" (2) and "AAA" (2) Simultaneously

Note: Please note battery orientation diagrams

in the instructions.

Charging Time:

(estimate

s:	Battery	Capacity	Estimated
d)	(NiMH)	(mAh)	(time)
	AA	1300-2000	5-7 hrs
	AA	2000-2400	7-9 hrs
	AAA	500-800	4-6 hrs

Shutoff Mechanism: Delta V Detection

Timer Control ~11 hrs

Charging Current: "AA" 260-300mA

"AAA" 120-150mA

Trickle Charge: None

Input Rating: 110-240VAC, 50/60Hz, 6W

Typical Weight: 107 grams

Dimensions (mm): 115 x 71 x 62 (H x L x W)

Safety Features: Reverse Polarity Protection

Bad Battery Detection Primary Battery Detection Delta V Charging Cut Off

Safety Timer to Prevent Overcharge

Important Notice

This datasheet contains information specific to products manufactured at the time of its publication.

© 2017 Energizer Brands, LLC

Contents herein do not constitute a warranty.

